# **BGA7017**

## 30 MHz to 6000 MHz broadband gain block

Rev. 4 — 27 March 2013

Objective data sheet

### 1. Product profile

#### 1.1 General description

The BGA7017 MMIC is a Darlington amplifier, available in a low-cost surface-mount package. It delivers 16.5 dBm output power at 1 dB gain compression and superior performance up to 6000 MHz, with minimal external components.

#### 1.2 Features and benefits

- 30 MHz to 6000 MHz frequency operating range
- 13 dB small signal gain at 2 GHz
- 16.5 dBm output power at 1 dB gain compression at 1000 MHz
- IP3<sub>O</sub>: 29.3 dBm at 2000 MHz
- Integrated active biasing
- 5 V single supply operation
- Industry standard SOT89 package
- ESD protection at all pins
- Flat (1.5 dB) gain response 100 MHz to 5500 MHz

#### 1.3 Applications

- Wireless infrastructure (base station, repeater, point-to-point backhaul systems)
- Radar
- Instrumentation

- Industrial applications
- E-metering
- Satellite Master Antenna TV (SMATV)

#### 1.4 Quick reference data

Table 1. Quick reference data

Unless otherwise specified input and output impedances terminated to 50  $\Omega$ ;  $V_{CC}$  = 5 V;  $T_{case}$  = 25  $^{\circ}$ C

Symbol	Parameter	Conditions		Min	Тур	Max	Unit
Icc	supply current			-	87	100	mΑ
f	frequency		[1]	30	-	6000	MHz
$G_p$	power gain	f = 2000 MHz		11	13	15	dB
$P_{L(1dB)}$	output power at 1 dB gain compression	f = 2000 MHz		13.5	15.5	-	dBm
IP3 <sub>O</sub>	output third-order intercept point	f = 2000 MHz	[2]	27	29.3	-	dBm

<sup>[1]</sup> Operation outside this range is possible but not guaranteed.

<sup>[2] -13</sup> dBm/tone < 4 GHz; -20 dBm/tone > 4 GHz; 1 MHz tone spacing.



#### 30 MHz to 6000 MHz broadband gain block

### 2. Pinning information

Table 2. Pinning

Pin	Description	Simplified outline	Graphic symbol
1	V <sub>CC</sub> /RF_OUT	Ш	
2	GND	[2]	,
3	RF_IN	[1]	3 7 2 sym130


- [1] This pin is DC-coupled and requires an external DC-blocking capacitor.
- [2] The center metal base of the SOT89 also functions as heatsink for the amplifier.

### 3. Ordering information

Table 3. Ordering information

Type number	Package					
	Name	Description	Version			
BGA7017	-	plastic surface-mounted package; exposed die pad for good heat transfer; 3 leads	SOT89			

## 4. Functional diagram



#### 30 MHz to 6000 MHz broadband gain block

### 5. Limiting values

Table 4. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).

Symbol	Parameter	Conditions	Min	Max	Unit
$V_{\text{CC}(\text{RF})}$	RF supply voltage		-	6.0	V
$P_{i(RF)}$	RF input power		-	13	dBm
$T_{\text{case}}$	case temperature		-40	+85	°C
$T_j$	junction temperature		-	125	°C
V <sub>ESD</sub>	electrostatic discharge voltage	Human Body Model (HBM); according to JEDEC standard 22-A114E	-	2000	V
		Charged Device Model (CDM); according to JEDEC standard 22-C101B	-	500	V

### 6. Thermal characteristics

Table 5. Thermal characteristics

Symbol	Parameter	Conditions	Тур	Unit
$R_{th(j\text{-}c)}$	thermal resistance from junction to case	$T_{case}$ = 85 °C; $V_{CC}$ = 5 V; $I_{CC}$ = 87 mA	60	K/W

### 7. Static characteristics

Table 6. Characteristics

Unless otherwise specified input and output impedances terminated to 50  $\Omega$ ;  $V_{\rm CC}$  = 5 V;  $T_{\rm case}$  = 25  $^{\circ}$ C.

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
$V_{CC}$	supply voltage		4.75	5.0	5.25	V
I <sub>CC</sub>	supply current		-	87	100	mΑ

### 30 MHz to 6000 MHz broadband gain block

## 8. Dynamic characteristics

Table 7. Characteristics

Unless otherwise specified input and output impedances terminated to 50  $\Omega$ ;  $V_{CC}$  = 5 V;  $T_{case}$  = 25  $^{\circ}$ C; see <u>Section 10</u> "Application information"; unless otherwise specified.

Symbol	Parameter	Conditions		Min	Тур	Max	Unit
f	frequency		[1]	30	-	6000	MHz
ΔG	gain variation	100 MHz to 5500 MHz		-	1.5	-	dB
$G_p$	power gain	f = 30 MHz		-	11.2	-	dB
		f = 100 MHz		-	13.5	-	dB
		f = 1 GHz		11	13.2	15	dB
	f = 2 GHz f = 3 GHz	f = 2 GHz		11	13	15	dB
		f = 3 GHz		-	13.8	-	dB
		f = 4 GHz		-	14.5	-	dB
		f = 5 GHz		-	14.5	-	dB
		f = 5.5 GHz		11	13	15	dB
		f = 6 GHz		-	9.8	-	dB
$P_{L(1dB)} \\$	output power at 1 dB gain compression	f = 30 MHz		-	18.3	-	dBm
		f = 100 MHz		-	18.5	-	dBm
		f = 1 GHz		-	16.5	-	dBm
		f = 2 GHz		13.5	15.5	-	dBm
		f = 3 GHz		-	14.7	-	dBm
		f = 4 GHz		-	11.7	-	dBm
		f = 5 GHz		-	9	-	dBm
		f = 6 GHz		-	5	-	dBm
IP3 <sub>0</sub>	output third-order intercept point	f = 30 MHz	[2]	-	34.7	-	dBm
		f = 100 MHz	[2]	-	34.6	-	dBm
		f = 1 GHz	[2]	-	30.8	-	dBm
		f = 2 GHz	[2]	27	29.3	-	dBm
		f = 3 GHz	[2]	-	27	-	dBm
		f = 4 GHz	[2]	-	23.5	-	dBm
		f = 6 GHz	[2]	-	15.5	-	dBm
NF	noise figure	f = 100 MHz		-	7.6	-	dB
		f = 2 GHz		-	6	-	dB
$RL_{in}$	input return loss	f = 30 MHz		-	4.2	-	dB
		f = 100 MHz		-	12.8	-	dB
		f = 1 GHz		-	11.5	-	dB
		f = 2 GHz		-	8	-	dB
		f = 3 GHz		-	7.7	-	dB
		f = 4 GHz		-	6.5	-	dB
		f = 6 GHz		-	2.5	-	dB

#### 30 MHz to 6000 MHz broadband gain block

Table 7. Characteristics ...continued

Unless otherwise specified input and output impedances terminated to 50  $\Omega$ ;  $V_{CC}$  = 5 V;  $T_{case}$  = 25  $^{\circ}$ C; see <u>Section 10</u> <u>"Application information"</u>; unless otherwise specified.

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
$RL_{out}$	output return loss	f = 30 MHz	-	4.5	-	dB
	f = 100 MHz	-	13.5	-	dB	
	f = 1 GHz	-	11.5	-	dB	
	f = 2 GHz	-	11.2	-	dB	
		f = 3 GHz	-	12	-	dB
		f = 4 GHz	-	8.7	-	dB
		f = 6 GHz	-	12.5	-	dB
$\alpha_{2H}$	second harmonic level	$P_i = -5 \text{ dBm}$ ; $F_o = 2 \text{ GHz}$	-	-43	-	dBc
S <sub>12</sub>	reverse transmission coefficient	10 MHz to 10 GHz	-	<20	-	dB
K	Rollett stability factor	10 MHz to 10 GHz	1	-	-	
$\Delta G/\Delta T$	gain variation with temperature	$-40$ °C to +85 °C; $F_o$ = 2 GHz	-	-0.006	-	dB/K

<sup>[1]</sup> Operation outside this range is possible but not guaranteed.

### 9. Moisture sensitivity

Table 8. Moisture sensitivity level


Test methodology	Class
JESD-22-A113	1

<sup>[2] -13</sup> dBm/tone < 4 GHz; -20 dBm/tone > 4 GHz; 1 MHz tone spacing.

30 MHz to 6000 MHz broadband gain block


## 10. Application information

#### 10.1 Evaluation board





### 10.2 Evaluation board parameters

#### 10.2.1 Output power, current as a function of input power




### 30 MHz to 6000 MHz broadband gain block






#### 30 MHz to 6000 MHz broadband gain block


#### 10.2.2 Gain characteristics







#### 30 MHz to 6000 MHz broadband gain block


### 10.2.3 Frequency characteristics





#### 30 MHz to 6000 MHz broadband gain block





#### 30 MHz to 6000 MHz broadband gain block





Fig 12. output power at 1 dB gain compression as a function of frequency over temperature



### 30 MHz to 6000 MHz broadband gain block

## 10.3 Evaluation board layout and components




Table 9. Evaluation board components

Designator	Description	Manufacturer Part Number	Manufacturer
C1	Do not populate	-	-
C2	Do not populate	-	-
C3	10 nF	GRM155R71E103KA01D	Murata
C4	1 μF	GRM155R60J105ME19D	Murata
C5	1000 pF	GRM1555C1H102JA01	Murata
C6	100 pF	GRM1555C1H101JA01	Murata
J1	CON-SMA-2	142-0711-821	Johnson
J2	CON-SMA-2	142-0711-821	Johnson
J3	CON-3PIN	PEG3SS-PBQ	Mueller
L1	390 nH	0603CS-R39XJL	COILCRAFT
L2	Do not populate	-	-
U1	BGA7017	BGA7017	NXP

### 30 MHz to 6000 MHz broadband gain block

### 11. Package outline

Plastic surface-mounted package; exposed die pad for good heat transfer; 3 leads

SOT89




Fig 15. Package outline SOT89

**BGA7017 NXP Semiconductors** 

### 30 MHz to 6000 MHz broadband gain block

### 12. Abbreviations

#### Table 10. Abbreviations

Acronym	Description
ESD	ElectroStatic Discharge
HTOL	High Temperature Operating Life
MMIC	Monolithic Microwave Integrated Circuit

## 13. Revision history

#### Table 11. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes
BGA7017 v.4	20130327	Objective data sheet	-	BGA7017 v.3
Modifications:	<ul> <li>Updated the throughout th</li> </ul>	"power gain" values and the "o ne document.	utput third-order inte	rcept point" values
BGA7017 v.3	20121030	Objective data sheet	-	BGA7017 v.2
Modifications:	Section 12 up	odated to include 11 new figure	es.	
BGA7017 v.2	20120913	Objective data sheet	-	BGA7017 v.1
BGA7017 v.1	20110505	Objective data sheet	-	-

#### 30 MHz to 6000 MHz broadband gain block

### 14. Legal information

#### 14.1 Data sheet status

Document status[1][2]	Product status[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

- [1] Please consult the most recently issued document before initiating or completing a design
- [2] The term 'short data sheet' is explained in section "Definitions"
- [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <a href="http://www.nxp.com">http://www.nxp.com</a>.

#### 14.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

#### 14.3 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk

**Applications** — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <a href="http://www.nxp.com/profile/terms">http://www.nxp.com/profile/terms</a>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

BGA7017

#### 30 MHz to 6000 MHz broadband gain block

**Export control** — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any

liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

**Quick reference data** — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

**Translations** — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

#### 14.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

#### 15. Contact information

For more information, please visit: http://www.nxp.com

For sales office addresses, please send an email to: salesaddresses@nxp.com

**BGA7017 NXP Semiconductors** 

### 30 MHz to 6000 MHz broadband gain block

### 16. Contents

1	Product profile	1
1.1	General description	1
1.2	Features and benefits	
1.3	Applications	
1.4	Quick reference data	1
2	Pinning information	2
3	Ordering information	2
4	Functional diagram	2
5	Limiting values	3
6	Thermal characteristics	3
7	Static characteristics	3
8	Dynamic characteristics	4
9	Moisture sensitivity	
10	Application information	6
10.1	Evaluation board	6
10.2	Evaluation board parameters	6
10.2.1	Output power, current as a function	
	of input power	
10.2.2	Gain characteristics	
10.2.3	Frequency characteristics	
10.3	Evaluation board layout and components	. 12
11	Package outline	. 13
12	Abbreviations	. 14
13	Revision history	. 14
14	Legal information	. 15
14.1	Data sheet status	. 15
14.2	Definitions	. 15
14.3	Disclaimers	
14.4	Trademarks	
15	Contact information	. 16
16	Contents	17

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.